Paramagnetic and diamagnetic states in two-dimensional

Josephson-junction arrays

Cinzia De Leo and Giacomo Rotoli‡

Dipartimento di Energetica and ‡Unit¶ di Ricerca INFM,

Universit¶ di L'Aquila, ITALY

(Dated: June 25, 2002)

**Abstract** 

Many experiments on high-temperature superconductors have shown paramagnetic behavior

when the sample is field cooled. The paramagnetism was first attributed to a d-wave order pa-

rameter creating  $\pi$ -junctions in the samples. However, the same effect was later discovered in

traditional low-temperature superconductors and conventional Josephson-junction arrays which

are s-wave. By simulating both conventional and mixed  $\pi$ /conventional Josephson-junction arrays

we determine that differences exist which may be sufficient to clearly identify the presence (or

absence) of  $\pi$ -junctions. In particular the  $\pi$ -junctions cause a symmetry breaking providing a

measurable signature of their presence in sample.

PACS numbers: 74.50+r, 74.72-h, 75.20 -g

1

In recent years a signi¯cant discussion in the superconductivity ¯eld was devoted to the paramagnetic response in ¯eld-cooled samples, the so-called paramagnetic Meissner e®ect (PME), [1]. PME was ¯rst observed in high- $T_c$  ceramic materials [1{3}] and then also in low  $T_c$  samples [4, 5]. A mechanism to explain the e®ect was introduced by Sigrist and Rice [6] where PME was due to the presence of ¼-junctions in the multiple-connected network of junctions formed by the superconducting grains in the high- $T_c$  ceramic. ¼-junctions are Josephson junctions formed between superconductors with unconventional pairing which cause a ¼ shift in the phase-current relation [7, 8]. Unconventional pairing, such as a d-wave order parameter, was introduced to explain the properties of high- $T_c$  ceramic materials [9]. PME was taken as strong evidence for a d-wave order parameter [6, 10]. Multiple-connectiveness and ¼-junctions were soon shown to give a paramagnetic response in simulated Josephson junction arrays by Dominguez, Jagla and Balseiro [11].

The discovery of PME in conventional low-T<sub>c</sub> (LTC) samples shows that PME cannot always be attributed to ¼-junction because they are present only in d-wave superconductors (or in unconventional superconductor-ferromagnet systems [8]). New explanations such as a giant °ux state [12], °ux compression [13] and surface states [14] have been introduced. The common feature was that PME in LTC samples is described as non-equilibrium phenomenon.

Very recently a new experiment was devised to test the connection between multi-connectiveness and PME in conventional systems. A square array of LTC junctions was <code>-eld</code> cooled and shown to be predominantly paramagnetic [15]; this paper also proposed a qualitative explanation for the <code>e®ect</code>. A subsequent analysis performed by numerical simulations of the arrays con <code>-rmed</code> the presence of PME in LTC arrays [16]. On this basis the essential ingredients of PME appears to be multiple-connectiveness rather than the presence of ¼-junction or non-equilibrium <code>e®ects</code>.

It is clear that simulated Josephson-junction arrays both with[11] and without [16] ¼-junctions show PME. Here we investigate by means of numerical simulations the di®erences between the two cases and the true role of the ¼-junctions. We also suggest an experimental signature of the presence of ¼-junctions in ¯eld-cooled array samples.

The array is described by means of a full mutual inductance model similar to that used in ref. [16]. The main di®erence is the presence of some %-junction, i.e., Josephson junctions where supercurrent is proportional to  $\sin('+\%)$  instead of  $\sin'$  (cf. Fig. 1). The dynamics of an NxN array are described by the following equations[16, 18, 19]:

$$\frac{L}{2\frac{L}{4}} (1 + \Xi) \sin(-+\tilde{A}) + \sqrt{\frac{L}{-C}} + \tilde{R} = \hat{K} \hat{L}^{i-1} m:$$
 (1)

Here time is normalized to a cell frequency (!  $^{i}$   $^{2}$  =  $^{L}$ C), with  $^{L}$ 0 the self inductance of the elementary loops formed of the array C the junction capacitance.  $^{-}$ C is the Stewart-McCumber parameter,  $^{-}$ C =  $^{2}$ 4 $^{I}$ 1 $^{O}$ C= $^{\odot}$ 0 $^{O}$ 6 where  $^{I}$ 0 is the (mean) Josephson critical current for the junctions in the array,  $^{\odot}$ 0 is the  $^{\circ}$ 0 ux quantum and G is the junction conductance.  $^{-}$ 1 is equal to  $^{2}$ 4 $^{L}$ 1 $^{0}$ 1 $^{O}$ 2 $^{\odot}$ 0. In represents the normalized loop magnetization (in unit of  $^{\odot}$ 0) which depends on frustation f, phase vector  $^{\cdot}$ 2 and the initial distribution of  $^{\circ}$ 1 ux quanta in the array loops n, here choosen to be a random integer vector [16].  $^{\circ}$ 1 and  $^{\circ}$ 2 are the matrixes carrying the mutual inductance coupling. The vector  $^{\circ}$ 4 has values of 0 or  $^{\circ}$ 4, providing a  $^{\circ}$ 4-shift to a subset of the junctions in the array. The concentration c of  $^{\circ}$ 4-junction [11] is the ratio between the number of  $^{\circ}$ 4-junctions and the total number of junctions. The vector  $^{\circ}$ 2 is a Gaussian variable with zero mean which we use to introduce disorder in the distribution of critical currents.

Here we suppose that in the array the contribution of the screening currents is not negligible, i.e.,  $^-_L > 1$  (cf. [3]). In particular we choose  $^-_L = 30$  and  $^-_C = 63$  (cf. refs. [15, 16]).

In both experiments [15] and previous simulations [16] it was shown that multiple-connectiveness e®ects are dominant for large  $^-$ eld, i.e., for large values of frustation f. To understand the e®ect of the ¼-shift we studied smaller values of frustation 0 < f < 1. In this region the behavior of an array without disorder and with all normal or all ¼-junctions roughly follows the single loop behavior [15{17}]which is described by

$$\frac{\mathbb{C}}{\mathbb{C}_0} - f = \frac{L}{2\frac{1}{4}} \sin(\frac{\frac{1}{4}}{2}n - \frac{\tilde{A}}{4} - \frac{\mathbb{C}}{\mathbb{C}_0})$$
 (2)

where © is the total °ux throught the loop. Solution of Eq. (2) gives the possible states for the total °ux © (or the current) in the single loop. For  $\tilde{A}=0$  Eq. (2) describe a single loop made by four conventional Josephson junction. There are four independent solutions which are obtained varying the integer n from zero to three. The (stable) lowest Gibbs energy state is diamagnetic for 0 < f < 1=2, i.e., the loop current is negative, generating a magnetic moment opposite to the external  $\bar{B}=0$  Eq. (2) describe a single loop current is negative a single loop current is negative.

the behavior: for the %-loop (a loop with an odd number of %-junctions) the lowest Gibbs energy state is paramagnetic for 0 < f < 1=2 and diamagnetic for 1=2 < f < 1.

In Ref. [16] we showed that conventional-array behavior can be qualitatively understood in terms of a model based on the single-loop behavior. We found that each loop in the array had a magnetization that was close to one of the lowest energy solutions of Eq. (2) for the isolated loop, with the number of loops of each type determining the overall magnetization. This simple picture also works for arrays with both conventional and ¼-junctions, with the number of possible solutions being increased because that Eq. (2) has additional solutions for the ¼-loops.

In order to compare conventional arrays with mixed conventional/ $\frac{1}{4}$  arrays, we <code>-rst</code> simulate the conventional arrays using the method of Ref. [16]. In Fig. 2a the magnetization of a 20 × 20 conventional array with f = 0.2 is shown. There are two single-loop magnetization states with a predominancy of diamagnetic states (light gray) over which a set of paramagnetic loops (dark gray) are randomly distributed. The histogram of loop magnetizations is shown in Fig. 3a and shows clearly only two peaks corresponding to two loop magnetizations. The mean magnetization is negative and small as expected for such small values of frustation accordingly to the Eq. (2) for the single loop; the exact value is m = -0.0027. As said above the values of the single peak averages can be obtained from Eq. (2); the small spread of the peaks is due to mutual inductance coupling.

In Fig. 2b a similar  $20 \times 20$  array with f=0.2 is shown in which 380 ¼-junctions have been introduced at random. This is equivalent to a concentration of ¼-junctions of c=0.45. The main di®erence with the case of coventional array is the presence of four magnetization states, two for each type of loop. We note that the new ¼-loop states are predominantly paramagnetic according to the symmetry shift discussed above. This, together with the lower number of conventional loops, is causing the reversal of the mean magnetization (here being m=+0.0018). This is the way in which a mixed array becomes paramagnetic for low values of frustation. Lower concentrations will make the array diamagnetic (i.e. the dependence on concentration is similar to that reported in Fig. 3b of Ref. [11] for a 3D system). For other values of f we note that the single loop symmetry is broken, i.e., for f<1=2 the array can be diamagnetic or paramagnetic depending on the distribution and number of ¼-loops.

From the preceding discussion, it is clear that there are at best only subtle di®erences

between a conventional array and an array containing a mixture of conventional and %-junctions. In the remainder of the paper we will show that when f=1=2 these di®erences are the most pronounced, and therefore f=1=2 is probably the best place to look experimentally in searching for evidence of %-junctions in non zero magnetic  $^-$ eld. When f=1=2 the problem is simpli $^-$ ed by the fact that the four lowest states shrink to three because the %-loop magnetization becomes zero. So one is confronted with only three peaks which are symmetrically distributed around the zero magnetization. In Fig. 4a this case is shown in a magnetization histogram. The central peak is the zero magnetization of %-loops and two symmetric lateral peaks are due to coventional loops. Symmetrical histogram structure is an optimal "signature", it is easily recognized with SSM and statistical  $^-$ Itering or image  $^-$ Itering techniques can be applied knowing the true distribution [21].

The central peak intensity is related to presence of %-loops. At c=0.3 (250 %-junctions) it becomes thinner preserving the same height. Then it decreases by about 10% at c=0.15 (126 %-junctions). Finally at c=0.05 (42 %-junctions) it decreases of about 60%.

In Fig. 4a a weak Gaussian disorder with a standard deviation of %=20% was introduced in the critical currents of the arrays similarly to Ref.[20]. This was added to shown that weak disorder does not change the three-peak structure of the magnetization histogram. For high values of the parameter  $^-$ L the nature of the magnetization states is discrete and this is preserved for weak disorder in the currents. Peak structure exists also with stronger disorder in the critical currents. In Fig. 4b we set %=80%[22] we see peaks enlarging until the tails of the single three distributions overlaps. It is observed that the remaining discrete structure is due again to the large  $^-$ L loops. Also we have simulated the array with the same parameters of Fig. 4b using a mean value of 1=3 for the %-junction critical current. The result is again similar to Fig. 4b but that central peak is lowered by roughly 13% and the histogram appears more enlarged.

In conclusion we would stress again how both conventional and mixed conventional/ $\frac{1}{4}$  arrays show a similar response when  $\frac{1}{4}$ -cooled. This response is related to the single loop solutions of Eq. (2). In low  $\frac{1}{4}$ -loops paramagnetism in mixed conventional/ $\frac{1}{4}$  arrays is the result of the paramagnetic behavior of  $\frac{1}{4}$ -loops. To quantify this e®ect for a disorderd system is di±cult because it depends on distribution and number of  $\frac{1}{4}$ -loops. On the other hand a noteworthy point is  $\frac{1}{4}$  = 1=2. Here the  $\frac{1}{4}$ -loops sets to zero current so it is possible from a measurement of the magnetization histogram to trace back the presence of  $\frac{1}{4}$ -loops in

the sample. For High- $T_c$  materials this experiment can be an important complement of the search for spontaneous currents in zero  $\bar{}$  eld [23]. Correlation between f=0 and f=1=2 would be of great interest permitting to estimate the  $\frac{1}{4}$ -loops content of the sample.

We warmly thank P. Barbara and C. J. Lobb for useful discussions and suggestion. Our thanks would be given also to A. P. Nielsen, F. Tafuri, G. Filatrella, S. Pagano and G. Costabile for their useful comments. We acknowledge <sup>-</sup>nancial support from MIUR COFIN2000 project "Dynamics and Thermodynamics of vortex structures in superconductive tunneling".

- W. Braunisch et al., Phys. Rev. Lett. 68, 1908, 1992; W. Braunisch et al., Phys. Rev. B 48, 4030, 1993.
- [2] J. R. Kirtley, A. C. Mota, M. Sigrist, T. M. Rice, J. Phys. Condens. Matter 10, L97, 1998.
- [3] E. L. Papadopoulou, P. Nordblad, P. Svedlindh, R. Schoneberger, R. Gross, Phys. Rev. Lett. 82, 173, 1999.
- [4] D. J. Thompson, M. S. M. Minhaj, L. E. Wenger, J. T. Chen, Phys. Rev. Lett. 75, 529, 1995.
- [5] P. Kostic et al., Phys. Rev. B 53, 791, 1996; A. K. Geim, S. V. Dubonos, J. G. S. Lok, M. Henini and J. C. Mann, Nature 396, 144, 1998.
- [6] M. Sigrist and T. M. Rice, J. Phys. Soc. Jpn. 61, 4283, 1992
- [7] D. J. Van Harlingen, Rev. Mod. Phys. 67, 515, 1995.
- [8] V. V. Ryazanov et al., Phys.Rev.Lett. 86, 2427, 2001.
- [9] J. Annett, N. Goldenfeld and S. R. Renn, Phys. Rev. B 43, 2778, 1991.
- [10] M. Sigrist and T. M. Rice, Rev. Mod. Phys. 67, 491, 1995.
- [11] D. Dominguez, E. A. Jagla and C. A. Balseiro, Phys. Rev. Lett. 72, 2773, 1994.
- [12] A. E. Koshelev and A. I. Larkin, Phys. Rev. B 52, 13559, 1995.
- [13] P. S. Deo, V. A. Schweigert, F. M. Peeters and A. K. Geim, Phys. Rev. Lett. 79, 4653, 1997;
  V. V. Moshchalkov, X. G. Qiu and V. Bruyndoncx, Phys. Rev. B 55, 11793, 1997.
- [14] P. S. Deo, V. A. Schweigert and F. M. Peeters, Phys. Rev. B 59, 6039, 1999.
- [15] A. P. Nielsen, A. B. Cawthorne, P. Barbara, F. C. Wellstood, C. J. Lobb, R. S. Newrock and M. G. Forrester, Phys. Rev. B 62, 14380, 2000.
- [16] C. De Leo, G. Rotoli, P. Barbara, A. P. Nielsen and C. J. Lobb, Phys. Rev. B 64, 144518, 2001.

- [17] F. Araújo-Moreira, P. Barbara, A. B. Cawthorne, C. J. Lobb, Phys. Rev. Lett. 78, 4625, 1997;Phys. Rev. B 60, 7489, 1999.
- [18] C. De Leo and G. Rotoli, Studies of High Temperature Superconductors (NOVA publishing in press), vol. 39, ed.s A. V. Narlikar and F. Araújo-Moreira, see web site: http://ing.univaq.it/energeti/research/Fisica/supgru.htm
- [19] C. De Leo and G. Rotoli, Supercond. Sci. Technol. 15, 111, 2002.
- [20] G. Filatrella, C. De Leo and G. Rotoli, Phys. Lett. A 270, 195, 2000.
- [21] J. R. Kirtley and J. P. Wikswo, Annu. Rev. Mater. Sci. 29, 117, 1999.
- [22] Note that points in the tails of Gaussian distribution of the currents can pick out negative values, so reverting some  $\pi$ -junction in normal junction and viceversa. Statistical tests shown that the number is however again balanced around c = 0.45.
- [23] F. Tafuri and J. R. Kirtley, Phys. Rev. B 62, 13934, 2000.

## Figure Captions

- Fig. 1 Two-dimensional Josephson junction array with a random distribution of ¼-junctions. The gray loops represent the ¼-loops, i.e., loops with an odd number of ¼-junctions. The <sup>-</sup>gure is just the top-left corner of the mixed array in Fig. 2b.
- Fig. 2 Simulated magnetization of a  $20 \times 20$  array at f = 0.2 with  $^-L = 30$  and  $^-C = 63$ : a) without ¼-junctions, light gray represents diamagnetic loops, gray paramagnetic ones; b) with ¼-junctions at a concentration of c = 0.45 white and light gray represents diamagnetic loops, gray and dark gray paramagnetic ones.
- Fig. 3 Magnetization histogram of a 20  $\times$  20 plane array at f = 0:2 with  $^-$ <sub>L</sub> = 30 and  $^-$ <sub>C</sub> = 63: a) distribution without ¼-junctions; b) distribution with ¼-junctions at a concentration of c = 0:45.
- Fig. 4 Magnetization histogram of a 20  $\times$  20 plane array at f = 0:5 with  $^-L$  = 30,  $^-C$  = 63 and ¼-junctions distribution at c = 0:45: a) e®ect of a weak disorder in the current distribution (¾ = 20%); b) the same for a stronger disorder(¾ = 80%).





Fig.1 De Leo & Rotoli






Fig.2, De Leo & Rotoli




Fig.3, De Leo & Rotoli




Fig.4, De Leo & Rotoli